

MODEL: L245

Solar Illuminated House Numbers | 3 Colours | AVENUE

For more information visit

hoselink.com.au

or call

1300 900 617

Cultivating Connections



youtube.com/hoselink

User Manual

3 Colours | AVENUE

MODEL: L245
Solar Illuminated House Numbers |

HOSELINK

HOSELINK

Kit Contents

- 1 x Solar panel
- 1 x Number/Letter
- 2 x Screws
- 2 x Masonry plugs

Assembly

Slot and click into place the letter or number into the solar light panel by lining up the grooves. To ensure this is done correctly, the number or letter should be facing out, so it is able to be read.

Lighting Modes

Once activated, the light automatically turns on at dusk and switches off at dawn. To activate the light, press the button on the base of the solar panel. Test by covering the solar panel completely to check that the light comes on.

The light is now ready for use. This light includes 3 different colour options as well as the ability to adjust the brightness.

Colour Options:

- 1 Warm white
- 2 Cool white
- 3 Blue

Brightness:

- 1 Low
- 2 High

To adjust the colour or brightness simply toggle the relevant switch located on the bottom of the light.

Product Installation

STEP 1 Find a suitable location

Solar lights need access to direct sunlight for optimum results; preferably 6-8 hours per day.

STEP 2 Install the light

Installation - Option 1

Using adhesive outdoor tape.

Adhere using Hoselink Outdoor Acrylic Double-Sided Tape (SKU L100), sold separately. Be sure to stick the tape onto the back of the light.

Installation - Option 2

Using supplied hardware.

Remove the screw plate from the rear of the solar panel to use as a template.

Masonry installation.

Using an electric drill (hammer or rotary), make a hole with a 6mm masonry drill piece. Hammer the plug into place then secure the screw.

Timber installation.

Using an electric drill, make a hole with a 3mm drill piece then secure the screw (without the plug).

Be sure to clean the solar panel periodically to maintain optimal performance.

Specifications

Solar panel	4.86V/0.52W
LED Lumens	20 lumens (bright light)
Lithium Battery	2000mAh / 3.7V
Charge Time	16.3 hours
Working Time	48 hours
Number of Lights	12 LEDs (4 x warm, 4 x cool, 4 x blue)
Solar Panel Size	50mm x 85mm
Water Proof Rating	IP54
Light Size	94*52.5*180mm
Materials	ABS+UV